

865 Purchase Order Change Acknowledgment/Request - Seller Initiated

**X12/V4010/865: 865 Purchase Order Change Acknowledgment/Request - Seller
Initiated**

Version: 1.0 Final

Company:	Oshkosh Corporation
Created:	10/14/2014
Notes:	Please note: The EDI 865 is currently only available for Oshkosh Defense,

Defense Aftermarket and JLG and must be used in conjunction with the EDI 855 Accept with Changes at the detail level.

Table of Contents

865 Purchase Order Change Acknowledgment/Request - Seller Initiated	1
ISA Interchange Control Header	2
GS Functional Group Header	4
ST Transaction Set Header	6
BCA Beginning Segment for Purchase Order Change Acknowledgment	7
POC Loop Line Item Change	8
POC Line Item Change	9
PO3 Additional Item Detail	11
ACK Loop Line Item Acknowledgment	12
ACK Line Item Acknowledgment	13
SCH Loop Line Item Schedule	14
SCH Line Item Schedule	15
SE Transaction Set Trailer	16
GE Functional Group Trailer	17
IEA Interchange Control Trailer	18

865 Purchase Order Change Acknowledgment/Request - Seller Initiated

Functional Group=**CA**

Purpose: This Draft Standard for Trial Use contains the format and establishes the data contents of the Purchase Order Change Acknowledgment/Request - Seller Initiated Transaction Set (865) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to convey acceptance or rejection of changes to a previously submitted purchase order by the seller or to notify the buyer of changes initiated by the seller to a previously submitted purchase order by the seller.

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	ST	Transaction Set Header	M	1			Must use
020	BCA	Beginning Segment for Purchase Order Change Acknowledgment	M	1			Must use

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - POC					≥1		
010	POC	Line Item Change	O	1			Used
030	PO3	Additional Item Detail	O	25			Used
LOOP ID - ACK					104		
270	ACK	Line Item Acknowledgment	O	1			Used
LOOP ID - SCH					200		
305	SCH	Line Item Schedule	O	1			Used

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
030	SE	Transaction Set Trailer	M	1			Must use

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	GE	Functional Group Trailer	M	1			Must use
	IEA	Interchange Control Trailer	M	1			Must use

ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

User Option (Usage): Must use

Purpose: To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	Authorization Information Qualifier	M	ID	2/2	Must use
Description: Code to identify the type of information in the Authorization Information All valid standard codes are used. (Total Codes: 7)						
ISA02	I02	Authorization Information	M	AN	10/10	Must use
Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)						
ISA03	I03	Security Information Qualifier	M	ID	2/2	Must use
Description: Code to identify the type of information in the Security Information All valid standard codes are used. (Total Codes: 2)						
ISA04	I04	Security Information	M	AN	10/10	Must use
Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)						
ISA05	I05	Interchange ID Qualifier	M	ID	2/2	Must use
Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified All valid standard codes are used. (Total Codes: 38)						
ISA06	I06	Interchange Sender ID	M	AN	15/15	Must use
Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element						
ISA07	I05	Interchange ID Qualifier	M	ID	2/2	Must use
Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified All valid standard codes are used. (Total Codes: 38)						
ISA08	I07	Interchange Receiver ID	M	AN	15/15	Must use
Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them						
ISA09	I08	Interchange Date	M	DT	6/6	Must use
Description: Date of the interchange						
ISA10	I09	Interchange Time	M	TM	4/4	Must use

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
		Description: Time of the interchange				
ISA11	I10	Interchange Control Standards Identifier	M	ID	1/1	Must use
		Description: Code to identify the agency responsible for the control standard used by the message that is enclosed by the interchange header and trailer All valid standard codes are used. (Total Codes: 1)				
ISA12	I11	Interchange Control Version Number	M	ID	5/5	Must use
		Description: Code specifying the version number of the interchange control segments All valid standard codes are used. (Total Codes: 14)				
ISA13	I12	Interchange Control Number	M	N0	9/9	Must use
		Description: A control number assigned by the interchange sender				
ISA14	I13	Acknowledgment Requested	M	ID	1/1	Must use
		Description: Code sent by the sender to request an interchange acknowledgment (TA1) All valid standard codes are used. (Total Codes: 2)				
ISA15	I14	Usage Indicator	M	ID	1/1	Must use
		Description: Code to indicate whether data enclosed by this interchange envelope is test, production or information All valid standard codes are used. (Total Codes: 3)				
ISA16	I15	Component Element Separator	M		1/1	Must use
		Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator				

GS Functional Group Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

User Option (Usage): Must use

Purpose: To indicate the beginning of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS01	479	Functional Identifier Code	M	ID	2/2	Must use
Description: Code identifying a group of application related transaction sets						
CodeList Summary (Total Codes: 240, Included: 1)						
Code Name						
CA Purchase Order Change Acknowledgment/Request - Seller Initiated (865)						
GS02	142	Application Sender's Code	M	AN	2/15	Must use
Description: Code identifying party sending transmission; codes agreed to by trading partners						
GS03	124	Application Receiver's Code	M	AN	2/15	Must use
Description: Code identifying party receiving transmission; codes agreed to by trading partners						
GS04	373	Date	M	DT	8/8	Must use
Description: Date expressed as CCYYMMDD						
GS05	337	Time	M	TM	4/8	Must use
Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)						
GS06	28	Group Control Number	M	N0	1/9	Must use
Description: Assigned number originated and maintained by the sender						
GS07	455	Responsible Agency Code	M	ID	1/2	Must use
Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480						
All valid standard codes are used. (Total Codes: 2)						
GS08	480	Version / Release / Industry Identifier Code	M	AN	1/12	Must use
Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed						
CodeList Summary (Total Codes: 39, Included: 1)						

<u>Code</u>	<u>Name</u>
004010	Draft Standards Approved for Publication by ASC X12 Procedures Review Board through October 1997

Semantics:

1. GS04 is the group date.
2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

ST Transaction Set Header

Pos: 010	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use

Description: Code uniquely identifying a Transaction Set

CodeList Summary (Total Codes: 298, Included: 1)

Code Name

865 Purchase Order Change Acknowledgment/Request - Seller Initiated

ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
------	-----	--------------------------------	---	----	-----	----------

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Semantics:

1. The transaction set identifier (ST01) used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).

BCA Beginning Segment for Purchase Order Change Acknowledgment

Pos: 020	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 5

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Change Acknowledgment Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BCA01	353	Transaction Set Purpose Code	M	ID	2/2	Must use
		Description: Code identifying purpose of transaction set				
		CodeList Summary (Total Codes: 65, Included: 1)				
		<u>Code</u> <u>Name</u>				
		00 Original				
BCA02	587	Acknowledgment Type	O	ID	2/2	Used
		Description: Code specifying the type of acknowledgment				
		CodeList Summary (Total Codes: 15, Included: 4)				
		<u>Code</u> <u>Name</u>				
		AC Acknowledge - With Detail and Change				
		AT Accepted				
		RD Reject with Detail				
		RO Rejected With Counter Offer				
BCA03	324	Purchase Order Number	M	AN	1/22	Must use
		Description: Identifying number for Purchase Order assigned by the orderer/purchaser				
BCA04	328	Release Number	O	AN	1/30	Used
		Description: Number identifying a release against a Purchase Order previously placed by the parties involved in the transaction				
BCA06	373	Date	O	DT	8/8	Not used
		Description: Date expressed as CCYYMMDD				

Semantics:

1. BCA06 is the date assigned by the purchaser to purchase order.
2. BCA09 is the seller's order number.
3. BCA10 is the date assigned by the sender to the acknowledgment.
4. BCA11 is the date of the purchase order change request.
5. BCA12 is the order change acknowledgment date.

Loop Line Item Change

Pos: 010	Repeat: >1
Optional	
Loop: POC	Elements: N/A

User Option (Usage): Used

Purpose: To specify changes to a line item

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
010	POC	Line Item Change	O	1		Used
030	PO3	Additional Item Detail	O	25		Used
270		Loop ACK	O		104	Used
305		Loop SCH	O		200	Used

POC Line Item Change

Pos: 010	Max: 1
Detail - Optional	
Loop: POC	Elements: 7

User Option (Usage): Used

Purpose: To specify changes to a line item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
POC01	350	Assigned Identification	O	AN	1/20	Used
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
POC03	330	Quantity Ordered	O	R	1/15	Used
		Description: Quantity ordered				
POC04	671	Quantity Left to Receive	X	R	1/9	Used
		Description: Quantity left to receive as qualified by the unit of measure				
POC05	C001	Composite Unit of Measure	X	Comp		Used
		Description: To identify a composite unit of measure(See Figures Appendix for examples of use)				
POC05-01	355	Unit or Basis for Measurement Code	M	ID	2/2	Must use
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		All valid standard codes are used. (Total Codes: 794)				
POC06	212	Unit Price	X	R	1/17	Used
		Description: Price per unit of product, service, commodity, etc.				
POC08	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		CodeList Summary (Total Codes: 477, Included: 1)				
		Code Name				
		BP Buyer's Part Number				
POC09	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				

Syntax Rules:

1. C030405 - If POC03 is present, then POC04 and POC05 are required.
2. C0706 - If POC07 is present, then POC06 is required.
3. P0809 - If either POC08 or POC09 is present, then the other is required.
4. P1011 - If either POC10 or POC11 is present, then the other is required.
5. P1213 - If either POC12 or POC13 is present, then the other is required.
6. P1415 - If either POC14 or POC15 is present, then the other is required.
7. P1617 - If either POC16 or POC17 is present, then the other is required.
8. P1819 - If either POC18 or POC19 is present, then the other is required.

9. P2021 - If either POC20 or POC21 is present, then the other is required.
10. P2223 - If either POC22 or POC23 is present, then the other is required.
11. P2425 - If either POC24 or POC25 is present, then the other is required.
12. P2627 - If either POC26 or POC27 is present, then the other is required.

Semantics:

1. POC01 is the purchase order line item identification.

PO3 Additional Item Detail

Pos: 030	Max: 25
Detail - Optional	
Loop: POC	Elements: 6

User Option (Usage): Used

Purpose: To specify additional item-related data involving variations in normal price/quantity structure

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO302	373	Date	O	DT	8/8	Used
		Description: Date expressed as CCYYMMDD				
PO303	236	Price Identifier Code	X	ID	3/3	Used
		Description: Code identifying pricing specification All valid standard codes are used. (Total Codes: 164)				
PO304	212	Unit Price	O	R	1/17	Used
		Description: Price per unit of product, service, commodity, etc.				
PO305	639	Basis of Unit Price Code	X	ID	2/2	Used
		Description: Code identifying the type of unit price for an item All valid standard codes are used. (Total Codes: 91)				
PO306	380	Quantity	M	R	1/15	Must use
		Description: Numeric value of quantity				
PO308	352	Description	O	AN	1/80	Used
		Description: A free-form description to clarify the related data elements and their content				

Syntax Rules:

1. L040305 - If PO304 is present, then at least one of PO303 or PO305 is required.

Comments:

1. Some examples of price/quantity variations are: price in different units from the PO1 segment, price changes by date, or price changes by quantity (break and level).
2. PO307 defines the unit of measure for PO306.

Loop Line Item Acknowledgment

Pos: 270	Repeat: 104
Optional	
Loop: ACK	Elements: N/A

User Option (Usage): Used

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
270	ACK	Line Item Acknowledgment	O	1		Used

ACK Line Item Acknowledgment

Pos: 270	Max: 1
Detail - Optional	
Loop: ACK	Elements: 1

User Option (Usage): Used

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ACK01	668	Line Item Status Code	M	ID	2/2	Must use

Description: Code specifying the action taken by the seller on a line item requested by the buyer

CodeList Summary (Total Codes: 26, Included: 4)

<u>Code</u>	<u>Name</u>
IA	Item Accepted
IC	Item Accepted - Changes Made
ID	Item Deleted
IR	Item Rejected

Syntax Rules:

1. P0203 - If either ACK02 or ACK03 is present, then the other is required.
2. C0405 - If ACK04 is present, then ACK05 is required.
3. P0708 - If either ACK07 or ACK08 is present, then the other is required.
4. P0910 - If either ACK09 or ACK10 is present, then the other is required.
5. P1112 - If either ACK11 or ACK12 is present, then the other is required.
6. P1314 - If either ACK13 or ACK14 is present, then the other is required.
7. P1516 - If either ACK15 or ACK16 is present, then the other is required.
8. P1718 - If either ACK17 or ACK18 is present, then the other is required.
9. P1920 - If either ACK19 or ACK20 is present, then the other is required.
10. P2122 - If either ACK21 or ACK22 is present, then the other is required.
11. P2324 - If either ACK23 or ACK24 is present, then the other is required.
12. P2526 - If either ACK25 or ACK26 is present, then the other is required.
13. P2728 - If either ACK27 or ACK28 is present, then the other is required.
14. C282729 - If ACK28 is present, then ACK27 and ACK29 are required.

Semantics:

1. ACK29 Industry Reason Code may be used to identify the item status. In addition, it may be used in conjunction with ACK01 to further clarify the status.

Loop Line Item Schedule

Pos: 305	Repeat: 200
Optional	
Loop: SCH	Elements: N/A

User Option (Usage): Used

Purpose: To specify the data for scheduling a specific line-item

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
305	SCH	Line Item Schedule	O	1		Used

SCH Line Item Schedule

Pos: 305	Max: 1
Detail - Optional	
Loop: SCH	Elements: 4

User Option (Usage): Used

Purpose: To specify the data for scheduling a specific line-item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SCH01	380	Quantity	M	R	1/15	Must use
Description: Numeric value of quantity						
SCH05	374	Date/Time Qualifier	M	ID	3/3	Must use
Description: Code specifying type of date or time, or both date and time						
CodeList Summary (Total Codes: 1112, Included: 1)						
<u>Code</u> <u>Name</u>						
002 Delivery Requested						
SCH06	373	Date	M	DT	8/8	Must use
Description: Date expressed as CCYYMMDD						
SCH12	350	Assigned Identification	M	AN	1/20	Must use
Description: Alphanumeric characters assigned for differentiation within a transaction set						

Syntax Rules:

1. C0304 - If SCH03 is present, then SCH04 is required.
2. L080910 - If SCH08 is present, then at least one of SCH09 or SCH10 is required.
3. C0908 - If SCH09 is present, then SCH08 is required.
4. C1008 - If SCH10 is present, then SCH08 is required.

Semantics:

1. SCH12 is the schedule identification.

Comments:

1. SCH05 specifies the interpretation to be used for SCH06 and SCH07.

SE Transaction Set Trailer

Pos: 030	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	N0	1/10	Must use
		Description: Total number of segments included in a transaction set including ST and SE segments				
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

Comments:

1. SE is the last segment of each transaction set.

GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	Number of Transaction Sets Included	M	N0	1/6	Must use
		Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element				
GE02	28	Group Control Number	M	N0	1/9	Must use
		Description: Assigned number originated and maintained by the sender				

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	Number of Included Functional Groups	M	N0	1/5	Must use
		Description: A count of the number of functional groups included in an interchange				
IEA02	I12	Interchange Control Number	M	N0	9/9	Must use
		Description: A control number assigned by the interchange sender				